

Dual Relay Modules

AS6052-00

AS6053-00

Low Voltage

Low Voltage w/Isolator

AS6054-00 AS6055-00

High Voltage



R R AS6052-00



AS6053-00

Standard Features

- Provides two independently configurable Form C contacts per address.
- Contacts are rated as follow: AS6052/ AS6053: 2A @ 30 VDC / 0.5A @ 120 VAC AS6054/ AS6055: 8A @ 30VDC / 4.8A @ 250 VAC
- Up to 127 devices can be used on each SLC loop
- Visible Bi-colored LED is software controlled and can be programmed to blink red or green when polled. The LED can be latched on when activated. (For All Models)
- Yellow LED indicates a short circuit condition (AS6053 & AS6055 only)
- Programming is highly flexible providing 16 priority states plus zoning capability
- Operates on Class A or Class B SLC loop

Technical Specifications

Supply Voltage Nominal: 25.3-39 VDC

Average Current Consumption: 350µA (Typical), 405µA (Alarm)

Contacts: 2 Independently Controlled Form C AS6052/VF6053: 2A @ 30 VDC/ 0.5A @ 120 VAC

AS6054/VF6055: 8A @ 30 VDC/ 4.8A @ 250 VAC

SCI on Resistance: 40 ohm Max. (normal condition)

SCI Fault Detection Threshold: 12 Volts (Typical)

SCI Isolation Current (short circuit condition): 10mA (Typical)

Maximum Quantity per Loop: 127

Dimensions: 4.2" W x 4.7" H x 1.4" D

Mounting: 4" square electrical box

Relative Humidity: 90% RH Non-Condensing

UL Ambient Installation Temperature Range: 32° F to 120° F

Operation

The Dual Relay Modules have been designed to provide flexible and guick response to emergency conditions. The Avenger Systems Series allows independent control of two form C contacts for a variety of normally open and normally closed contact applications such as fan operation, elevator recall, door closure, and auxiliary notification.

Each Avenger Systems Series module provides independent control of two Form C contacts while utilizing one SLC (Signaling Line Circuit) address. The modules have a highly configurable programming algorithm that allows the user to set up groups of devices (zoning) for simultaneous operation of multiple AS6052, AS6053, AS6054, AS6055 modules. The operating parameters are maintained by the module and do not require individual communication with the control panel during the emergency condition to operate. The control panel broadcasts the control command on the SLC loop and the Avenger Series modules do the rest based on their custom configuration. Since mechanically latching relays are used within the Avenger Series modules, a separate 24VDC power source is not required.

Fire Detection System by Avenger, Las Vegas, Nevada 89141 U.S.A. I Phone: 1-702-513-4654 info@avengersystems.com I www.avengersystems.com